

MR2707-58

Serial Number: 10/765,039

Response to Office Action dated 5 April 2007

RECEIVED
CENTRAL FAX CENTER

SEP 05 2007

AMENDMENTS TO THE CLAIMS

This Listing of Claims will replace all prior versions, listing, of claims in the Specification.

LISTING OF CLAIMS:

1. (Original) A gamma voltage generator for generating a plurality of individually tunable gamma voltages corresponding to a symmetric gamma curve, the generator comprising:

a plurality of adjustable voltage sources for providing an adjustable common voltage and a plurality of adjustable voltages to further derive a common gamma voltage and a plurality of first gamma voltages therefrom; and

a mirror mapping circuit for mapping each of the plurality of first gamma voltages with the common gamma voltage as a reference to thereby generate a plurality of mapped voltages to further derive a plurality of second gamma voltages therefrom with the common gamma voltage as a center axis for the plurality of first and second gamma voltages distributed substantially symmetric to each other;

wherein the common gamma voltage and the plurality of first and second gamma voltages are provided for the gamma voltages corresponding to the gamma curve.

2. (Original) The gamma voltage generator of claim 1, wherein each of the plurality of adjustable voltage sources comprising:

MR2707-58

Serial Number: 10/765,039

Response to Office Action dated 5 April 2007

an adjustable resistive element; and

a gamma current flowing through the adjustable resistive element for generating one of the adjustable common voltage and the plurality of adjustable voltages.

3. (Original) The gamma voltage generator of claim 2, further comprising a current mirror for mirroring a reference current to thereby generate the gamma current.

4. (Original) The gamma voltage generator of claim 3, further comprising an adjustable current source for providing the reference current.

5. (Original) The gamma voltage generator of claim 4, wherein the adjustable current source comprises a second adjustable resistive element connected with a reference voltage for generating the reference current.

6. (Original) The gamma voltage generator of claim 4, wherein the adjustable current source comprises a reference resistor connected with an adjustable reference voltage for generating the reference current.

7. (Original) The gamma voltage generator of claim 1, wherein the mirror mapping circuit comprises a plurality of operational amplifiers each subtracting

MR2707-58

Serial Number: 10/765,039

Response to Office Action dated 5 April 2007

one of the plurality of first gamma voltages from double of the common gamma voltage to thereby generate corresponding one of the plurality of mapped voltages.

8. (Original) The gamma voltage generator of claim 1, wherein the mirror mapping circuit comprises a plurality of voltage converter each including:

a first current mirror having a first reference branch connected with the common gamma voltage and a first resistive element for generating a first current, and a first mirror branch for mirroring the first current to thereby generate a second current in a first ratio to the first current;

a second current mirror having a second reference branch connected with one of the plurality of first gamma voltages and a second resistive element for generating a third current, and a second mirror branch for mirroring the third current to thereby generate a fourth current in a second ratio to the third current; and

a third resistive element connected with the second and fourth currents for generating corresponding one of the mapped voltages proportional to a difference between the second and fourth currents.

9. (Original) The gamma voltage generator of claim 8, wherein the first, second and third resistive elements comprise a substantially same resistance.

MR2707-58

Serial Number: 10/765,039

Response to Office Action dated 5 April 2007

10. (Original) A method for generating a plurality of individually tunable gamma voltages corresponding to a symmetric gamma curve, the method comprising the steps of:

generating an adjustable common voltage and a plurality of adjustable voltages;

deriving a common gamma voltage and a plurality of first gamma voltages from the adjustable common voltage and the plurality of adjustable voltages, respectively;

mapping each of the plurality of first gamma voltages with the common gamma voltage as a reference to thereby generate a plurality of mapped voltages; and

deriving a plurality of second gamma voltages from the plurality of mapped voltages with the common gamma voltage as a center axis for the plurality of first and second gamma voltages distributed substantially symmetric to each other;

wherein the common gamma voltage and the plurality of first and second gamma voltages are provided for the gamma voltages corresponding to the gamma curve.

11. (Original) The method of claim 10, wherein the step of generating an adjustable common voltage and a plurality of adjustable voltages comprises the steps of:

MR2707-58

Serial Number: 10/765,039

Response to Office Action dated 5 April 2007

generating a plurality of gamma currents of a substantially same magnitude; and

generating the adjustable common voltage and the plurality of adjustable voltages each by a respective one of the plurality of gamma currents flowing through an adjustable resistive element.

12. (Original) The method of claim 11, further comprising the step of mirroring a reference current to thereby generate the plurality of gamma currents.

13. (Original) The method of claim 12, further comprising the step of applying a reference voltage to a second adjustable resistive element for generating the reference current.

14. (Original) The method of claim 12, further comprising the step of applying an adjustable reference voltage to a reference resistor for generating the reference current.

15. (Original) The method of claim 10, wherein the step of generating a plurality of mapped voltages comprises the steps of:

subtracting one of the plurality of first gamma voltages from the common gamma voltage to thereby generate a difference; and

MR2707-58

Serial Number: 10/765,039

Response to Office Action dated 5 April 2007

summing the difference and the common gamma voltage to thereby generate a corresponding mapped voltage.

16. (Original) The method of claim 10, wherein the step of generating a plurality of mapped voltages comprises the steps of:

generating a first current from the common gamma voltage;
generating a second current in a first ratio to the first current;
generating a third current from one of the plurality of first gamma voltages;
generating a fourth current in a second ratio to the third current; and
generating a corresponding mapped voltage from a difference between the second and fourth currents.

17. (Original) The method of claim 16, further comprising the steps of:

generating a first voltage from the second current with the first voltage in the first ratio to the common gamma voltage;
generating a second voltage from the fourth current with the second voltage in the second ratio to the one of the plurality of first gamma voltages; and
subtracting the second voltage from the first voltage to generate the corresponding mapped voltage.

MR2707-58

Serial Number: 10/765,039

Response to Office Action dated 5 April 2007

18. (Original) A gamma voltage generator for generating a plurality of individually tunable gamma voltages corresponding to a symmetric gamma curve, the generator comprising:

a current source for providing a reference current;

a current mirror for mirroring the reference current to generate a plurality of gamma currents; and

means for generating a common gamma voltage and a plurality of first and second gamma voltages proportional to the plurality of gamma currents with the common gamma voltage as a center axis for the plurality of first and second gamma voltages distributed substantially symmetric to each other;

wherein the common gamma voltage and the plurality of first and second gamma voltages are provided for the gamma voltages corresponding to the gamma curve.

19. (Original) The gamma voltage generator of claim 18, wherein the plurality of gamma currents have a substantially same magnitude.

20. (Original) The gamma voltage generator of claim 18, wherein the means for generating a common gamma voltage and a plurality of first and second gamma voltages comprises means for mapping the plurality of first gamma voltages to

MR2707-58

Serial Number: 10/765,039

Response to Office Action dated 5 April 2007

generate the plurality of second gamma voltages with the common gamma voltage as a center axis.

21. (Original) The gamma voltage generator of claim 18, wherein the current source comprises an adjustable resistive element connected with a reference voltage for generating the reference current.

22. (Original) The gamma voltage generator of claim 18, wherein the current source comprises a resistive element connected with an adjustable reference voltage for generating the reference current.

23. (Original) The gamma voltage generator of claim 18, wherein the means for generating a common gamma voltage and a plurality of first and second gamma voltages comprises means for transforming the plurality of gamma currents to the common gamma voltage and the plurality of first and second gamma voltages.

24. (Original) The gamma voltage generator of claim 20, wherein the means for mapping the plurality of first gamma voltages to generate the plurality of second gamma voltages comprises:

means for subtracting one of the plurality of first gamma voltages from the common gamma voltage to thereby generate a difference; and

MR2707-58

Serial Number: 10/765,039

Response to Office Action dated 5 April 2007

means for summing the difference and the common gamma voltage to thereby generate a corresponding second gamma voltage.

25. (Original) The gamma voltage generator of claim 20, wherein the means for mapping the plurality of first gamma voltages to generate the plurality of second gamma voltages comprises:

means for generating a first current in a first ratio to the common gamma voltage;

means for generating a second current in a first ratio to one of the plurality of first gamma voltages; and

means for generating a corresponding second gamma voltage in a third ratio to a difference between the first and second currents.

26. (Original) A method for generating a plurality of individually tunable gamma voltages corresponding to a symmetric gamma curve, the method comprising the steps of:

providing a reference current;

mirroring the reference current for generating a plurality of gamma currents; and

generating a common gamma voltage and a plurality of first and second gamma voltages proportional to the plurality of gamma currents with the common

MR2707-58

Serial Number: 10/765,039

Response to Office Action dated 5 April 2007

gamma voltage as a center axis for the plurality of first and second gamma voltages distributed substantially symmetric to each other;

wherein the common gamma voltage and the plurality of first and second gamma voltages are provided for the gamma voltages corresponding to the gamma curve.

27. (Original) The method of claim 26, further comprising the step of mapping the plurality of first gamma voltages to generate the plurality of second gamma voltages with the common gamma voltage as a center axis.

28. (Original) The method of claim 26, further comprising the step of applying the plurality of gamma currents each flowing through an adjustable resistive element to generate the common gamma voltage, one of the plurality of first gamma voltages, or one of the plurality of second gamma voltages.

29. (Original) The method of claim 26, further comprising the step of applying a reference voltage to an adjustable resistive element for generating the reference current.

30. (Original) The method of claim 26, further comprising the step of applying an adjustable reference voltage to a reference resistor for generating the reference current.

MR2707-58

Serial Number: 10/765,039

Response to Office Action dated 5 April 2007

31. (Original) The method of claim 27, wherein the step of generating the plurality of second gamma voltages comprises the steps of:

subtracting one of the plurality of first gamma voltages from the common gamma voltage to thereby generate a difference; and

summing the difference and the common gamma voltage to thereby generate a corresponding second gamma voltage.

32. (Original) The method of claim 27, wherein the step of generating the plurality of second gamma voltages comprises the steps of:

generating a first current from the common gamma voltage;

generating a second current in a first ratio to the first current;

generating a third current from one of the plurality of first gamma voltages;

generating a fourth current in a second ratio to the third current; and

generating a corresponding second gamma voltage from a difference between the second and fourth currents.

33. (Original) The method of claim 32, further comprising the steps of:
generating a first voltage from the second current with the first voltage in the first ratio to the common gamma voltage;

MR2707-58

Serial Number: 10/765,039

Response to Office Action dated 5 April 2007

generating a second voltage from the fourth current with the second voltage in the second ratio to the one of the plurality of first gamma voltages; and subtracting the second voltage from the first voltage to generate the corresponding mapped voltage.